





## NONEL® EZ DET 1.1B

### Nonelectric Blast Initiation System

#### Properties Cont.

##### Packaging

Length		Case Type	Quantity/ Case
meters	feet		
3.5	12	D*	100
4.5	16	D*	90
7	24	D*	70
9	30	DC	120
12	40	DC	120
15	50	DC	90
18	60	DC	90
24	80	DC	40
30	100	DC	40
37	120	DC	30

- Length rounded to nearest one-half meter.
- Case weight varies by length & delay; see case label for exact weight.
- \* Always shipped with 2 cases strapped together. Case dimension width doubles.

##### Case Dimensions

Detpak Case (DC)	48 x 45 x 26 cm	18 ¾ x 17 ¾ x 10 ¾ in
Detpak (D)	44 x 22 x 25 cm	17 ½ x 8 ¾ x 10 in

#### APPLICATION RECOMMENDATIONS - continued

- **ALWAYS** ensure that individual shock tubes remain aligned side by side in the connector channel and do not cross one over the another on insertion.
- **NEVER** use NONEL EZ DET units with detonating cord. The low strength surface detonator will not initiate detonating cord and may cause misfires.
- **NEVER** attempt to disassemble the delay detonator from the plastic EZ Connector block or use the detonator without the connector.
- **NEVER** place more than 6 shock tube leads into the plastic EZ Connector block. Misfires may result.
- **NEVER** pull, stretch, kink or put tension on shock tube such that the tube could break.
- **NEVER** splice NONEL EZ DET shock tube together to extend between holes.
- **NEVER** connect NONEL EZ DET units together until all holes have been primed, loaded and stemmed and the blast site has been cleared.

#### TRANSPORTATION, STORAGE AND HANDLING

- NONEL EZ Det must be transported, stored, handled and used in conformity with all federal, state, provincial and local laws and regulations.
- For maximum shelf life (3 years), NONEL EZ Det must be stored in a cool, dry, well ventilated magazine. Explosive inventory should be rotated. Avoid using new materials before the old. For recommended good practices in transporting, storing, handling and using this product, see the booklet "Prevention of Accidents in the Use of Explosive Materials" packed inside each case and the Safety Library Publications of the Institute of Makers of Explosives.

**ADDITIONAL INFORMATION – Visit [dynonobel.com](http://dynonobel.com) for Brochures and Case Studies related to this product.**

**Product Disclaimer:** Dyno Nobel Inc. and its subsidiaries disclaim any warranties with respect to this product, the safety or suitability thereof, or the results to be obtained, whether express or implied, INCLUDING WITHOUT LIMITATION, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE AND/OR OTHER WARRANTY. Buyers and users assume all risk, responsibility and liability whatsoever from any and all injuries (including death), losses, or damages to persons or property arising from the use of this product. Under no circumstances shall Dyno Nobel Inc. or any of its subsidiaries be liable for special, consequential or incidental damages or for anticipated loss of profits.